ED-WP-CB Data Sheet

Abstract

ED-WP-CB is a high-performance digital gate driver core developed by Firstack for NPC I-type /ANPC 3-level system. The gate driver adopts CPLD as the digitally controlled core, with complete protection functions and built-in fault management system, which uploads the converter's operating state to the master computer in real time, providing support for "big data management" for the failed converter site. Perfectly solving the two major problems of "turn-off timing sequence" and "large commutation circuit turn-off peak" in NPC I-type topology, the reliability of NPC topology can be comparable to 2-level, allowing customers to use NPC I-type /ANPC 3-level as same as 2-level.



Fig. 1 ED-WP-CB

Highlights:

- ✓ Multi-parallel of NPC/ANPC topology
- ✓ Rated voltage range:690-1250VAC
- ✓ Power range:1MW-10MW





Contents

Abstract1
Functional block diagram
Use steps and matters needing attention
Mechanical dimensions
LED status indication
Pin definition
Technical parameters
Function description
Short-circuit protection
• Undervoltage protection
• Muti-level turn-off (reserved)
• Short pulse suppression
• NTC sampling
Fault code return (reserved)
• Intelligent fault management system
Ordering information
Technical support
Legal disclaimer
Contact information



Functional block diagram



Fig. 2 Functional block diagram

Use steps and matters needing attention

Simple use steps of the gate driver are as follows:

1. Choose suitable gate driver

When use the gate driver, pay attention to the model of the IGBT module that the gate driver is adapted to. It is invalid for non-designated IGBT modules. Improper use may cause the gate driver and the module failure.

2. Install the gate driver on the IGBT module

Any treatment of IGBT modules or gate drivers should follow the general specifications for the protection of electrostatic sensitive devices required by the international standard IEC 60747-1, Chapter IX or European standard EN 61340-5-1.

If these specifications were ignored, both the IGBT

and the gate driver might be damaged.



3. Connect the gate driver to the control unit

Connect the gate driver connector to the control unit and provide a suitable power supply voltage for the gate driver.

4. Check the function of the gate driver

Check the gate voltage: for the turn-off state, the rated gate voltage is given in the corresponding data sheet; for the turn-on state, the voltage is 15V. Please also check the input current of the gate driver with and without a control signal. These tests should be performed prior to installation, as the gate terminals may not be accessible after installation.

5. Set up and test the power unit

Before starting the system, it is recommended to check each IGBT module with single pulse and double pulse test method separately. In particular, Firstack recommends that users ensure that the IGBT module does not exceed the operating range specified by SOA even under the worst conditions, as this is strongly dependent on the specific converter architecture.



Mechanical dimensions



Fig. 3 Mechanical dimensions(unit: mm)

Note: 1. The tolerance of the board thickness is $\pm 10\%$;

2. Other dimensional tolerances refer to GB/T1804-m;

3.All mounting holes in the diagram must be used as a fixing, otherwise the connector is likely to cause damage to the gate driver due to excessive insertion and extraction stress. At the same time, the mounting holes must be fixed with plastic studs or other insulating material studs, otherwise there is a risk of safety issue.

Number	Label	Manufacturer	Part Number	Recommended Matching Terminals
1	P1	Nextron	Z-230011830209	FC-30P
2	P8, P10, P12, P22, P23	WCON	WF3963-WSH12B02	WF3963-H12B01
3	P16	WCON	WF2501A-WSH15B02	WF2501A-H15B01
4	P18	WCON	WF2501A-WSH06B05	WF2501A-H06B01
5	P20, P21	JST	B2B-XH-A	XHP-2

Connector Manufacturer and Part Number

LED status indication



Fig. 4 Status indicator

For the convenience of customers, several LED status indicators are added on the Firstack gate driver board to facilitate customers to know the operating status of the gate driver board and converter. The specific explanation is as follows:

Number	Label	Interface	Note	Colour
1	D19	UV	Once undervoltage trigger is always on, unless restarted.	Red
2	D15	TEST	Light on when the primary power supply is normal and there is no fault, otherwise it turns off.	Green
3	D13	SC	Once short-circuit trigger is always on, unless restarted.	Red
4	D10	0Т	Once over-temperature trigger is always on unless restarted (reserved).	Red

Status Indicator

Pin definition

Р	PI pin definition:						
Pin	Name	Description	Pin	Name	Description		
1	NC	Free	2	V _{DC}	+15V power supply		
3	V _{DC}	+15V power supply	4	V _{DC}	+15V power supply		
5	GND	Primary side ground	6	SO	Fault summary		
7	GND	Primary side ground	8	GND	Primary side ground		
9	GND	Primary side ground	10	IN1	T1 transistor PWM signal		
11	GND	Primary side ground	12	PT1-1	External PT1 pin1		
13	PT1-2	External PT1 pin2	14	NC	Free		
15	GND	Primary side ground	16	IN2	T2 transistor PWM signal		
17	GND	Primary side ground	18	PT2-1	External PT2 pin1		
19	PT2-2	External PT2 pin2	20	NC	Free		
21	GND	Primary side ground	22	IN3	T3 transistor PWM signal		
23	GND	Primary side ground	24	IN4	T4 transistor PWM signal		
25	GND	Primary side ground	26	IN5	T5 transistor PWM signal		
27	GND	Primary side ground	28	IN6	T6 transistor PWM signal		
29	GND	Primary side ground	30	FOUT	Frequency output		

P8 pin definition:

Pin	Name	Description	Pin	Name	Description
1	Vcesat-T5	T5 detected signal	7	NC	The pin is removed
2	15V-T5	T5_15V	8	Vcesat-T1	T1 detected signal
3	OFF-T5	T5 turn-off signal	9	15V-T1	T1_15V
4	ACOM-T5	T5 GND	10	OFF-T1	T1 turn-off signal
5	ON-T5	T5 turn-on signal	11	ACOM-T1	T1 GND
6	NC	The pin is removed	12	ON-T1	T1 turn-on signal

P10 pin definition:

Pin	Name	Description	Pin	Name	Description
1	Vcesat-T3	T3 detected signal	7	NC	The pin is removed
2	15V-T3	T3_15V	8	Vcesat-T2	T2 detected signal
3	OFF-T3	T3 turn-off signal	9	15V-T2	T2_15V
4	ACOM-T3	T3 GND	10	OFF-T2	T2 turn-off signal
5	ON-T3	T3 turn-on signal	11	ACOM-T2	T2 GND
6	NC	The pin is removed	12	ON-T2	T2 turn-on signal



P12, P23 pin definition: Pin Description Pin Name Name Description 7 Vcesat-T4 T4 detected signal NC 1 The pin is removed 15V-T4 T4_15V 8 Vcesat-T6 T6 detected signal 2 9 3 OFF-T4 T4 turn-off signal 15V-T6 $T6_{15V}$ 4 ACOM-T4 T4 GND 10 OFF-T6 T6 turn-off signal T6 GND 5 ON-T4 11 T4 turn-on signal ACOM-T6 The pin is removed 12 6 NC ON-T6 T6 turn-on signal

P16 pin definition:

Pin	Name	Description	Pin	Name	Description
1	-15V-T4	T4 negative voltage	9	NTC9	Module 9 temperature signal
2	GND-T4	T4 GND	10	NC	The pin is removed
3	GND-T4	T4 GND	11	NC	The pin is removed
4	NTC1	Module 1 temperature signal	12	NC	The pin is removed
5	NTC3	Module 3 temperature signal	13	NTC10	Module 10 temperature signal
6	NTC4	Module 4 temperature signal	14	NTC12	Module 12 temperature signal
7	NTC6	Module 6 temperature signal	15	GND-T4	T4 GND
8	NTC7	Module 7 temperature signal			

P18 pin definition:

Pin	Name	Description	Pin	Name	Description
1	15V-T4	T4 15V	4	NTC5	Module 5 temperature signal
2	GND-T4	T4 GND	5	NTC8	Module 8 temperature signal
3	NTC2	Module 2 temperature signal	6	NTC11	Module 11 temperature signal

P20 pin definition:

Pin	Name	Description	Pin	Name	Description
1	PT1-1	External PT1 pin1	2	PT1-2	External PT1 pin2

P21 pin definition:

Pin	Name	Description	Pin	Name	Description
1	PT2-1	External PT2 pin1	2	PT2-2	External PT2 pin2

*The gate driver samples the temperature signals of 12 modules.

*NTCx is the temperature signal of module x.

Technical parameters

Absolute Maximum Ratings							
Parameter	Note	Min.	Max.	Unit			
V _{DC}	V_{DC} to GND		15.5	V			
Logic input and output voltages	Primary side, to GND	0	15.5	V			
SO output	Fault condition		500	mA			
Gate peak current			108	А			
Output power per channel	T _A =85°C		4	W			
Test valtage $(50 \text{Hz}/1 \text{min})$	Primary to secondary side	5700	4 W V _{RMS}				
Test voltage (30Hz/1mm)	Secondary to secondary side	D15.5Ve, to GND015.5Vtion500mA108A4Wsecondary side5700VRMSto secondary side5700VRMS ± 100 ± 250 kV/us-4085°CC2W	V _{RMS}				
CMTI		±100	±250	kV/us			
Operating temperature		-40	85	°C			
Gate resistance derating	40%@118°C		2W				
Storage temperature		-40	85	°C			

Recommended Operating Conditions

Parameters	Note	Min.	Тур.	Max.	Unit
V _{DC}			15		V
IN _X			15		V

Electrical Characteristics

Power supply	Note	Min	Тур	Max	Unit	
Power supply current	Without load, Note 1		0.47		А	
Coupling capacitance	Primary to secondary side, Note 2		12		pF	
Primary side power monitoring						
Threshold			13		V	
Input and output logic	:					
Input impedance			10		kΩ	
Turn-on threshold	15V PWM input, high turn on		8.3		V	
Turn-off threshold	15V PWM input, high turn on		4.8		V	
NTC output level			15		V	
SOx output potential	High normal, low fault (pulse)		15		V	
Short-circuit protection						
V _{CE} monitoring threshold			11.1		V	
Response time	T1, T4, Note 3		6.7		us	
	T2, T3, Note 3		8.0		us	
	T5, T6, Note 3		8.2		us	
Blocking time			90		ms	



Timing characteristics						
	T1, T4, Note 4	850		ns		
Turn-on delay Turn-off delay	T2, T3, Note 4	850		ns		
	T5, T6, Note 4	850		ns		
	T1, T4, Note 5	850		ns		
	T2, T3, Note 5	850	1	ns		
	T5, T6, Note 5	850		ns		
Rise time	T1, T4, Note 6	250		ns		
	T2, T3, Note 6	650		ns		
	T5, T6, Note 6	250		ns		
	T1, T4, Note 7	500		ns		
Fall time	T2, T3, Note 7	700		ns		
	T5, T6, Note 7	500		ns		
Output characteristics						
Gate turn-on voltage		15		V		
Gate turn-off voltage		-15		V		
~	T1, T4, T5, T6	4.7		kΩ		
Gate static impedance	T2, T3	10		kΩ		
Electrical isolation						
Creepage distance	Primary to secondary side, Note 8	15		mm		
Clearance distance	Primary to secondary side	14.5	;	mm		
NTC temperature acquisition						
NTC temperature		40	105	90		
acquisition range		-40	125	Ċ		
NTC signal interval time	Note 9	1		ms		
Fault output						
Fault signal indication time	Note 10	5		ms		
Dead time						
(T1&T3) (T2&T4) Dead	NT / 11	4				
time	note 11	4		us		
Short pulse suppression						
Short pulse filtering time	Note 12		400	ns		

Unless otherwise specified, all data are based on +25°C and V_{IN}=15V.

Note:

- 1. Power supply current: gate driver core connected to IGBT, no PWM input;
- 2. Coupling capacitance: the values of coupling capacitance are within the range of values given in the table;
- 3. Response time: the time from the occurrence of the fault to the start of soft shut down;

- 4. Turn-on delay: the time required to transmit the rising edge of the PWM signal input from the primary side to the rising edge of the gate driver of the secondary side when the IGBT is not connected;
- 5. Turn-off delay: the time required to transmit the falling edge of the PWM signal input from the primary side to the falling edge of the gate driver of the secondary side when the IGBT is not connected;
- 6. Rise Time: the amount of time from 10% of the gate turn-off voltage(-15V) to 90% of the gate turn-on voltage(+15V);
- 7. Fall Time: the amount of time from 90% of the gate turn-on voltage(+15V) to the gate turn-off voltage(-15V);
- 8. Creepage distance: refer to IEC61800-5-1-2007;
- 9. NTC signal interval time: the period of time that an NTC signal output waits for a high level from one NTC signal output to another NTC signal output;
- 10. Fault signal indication time: fault signal is high when normal, if the gate driver detects a fault, the fault signal first waits for low level for 5ms, then outputs the fault code;
- 11. Dead time: when the time set by the control board has no deadband or is less than 4µs, the driver board itself will have a 4µs deadband; when the time set by the control board is more than 4µs, it will be executed according to the control board time;
- 12. Short pulse filtering time: the maximum short pulse that can be filtered out is 400ns, which may be less than this value in practice.

Function description

Short-circuit protection

The driving circuit determines whether the IGBT is in a short-circuit state by detecting the collector voltage V_{CE} when the IGBT turns on.

The V_{CE} voltage is detected by high-voltage diodes. When the V_{CE} voltage exceeds the set threshold, the gate driver determines that the IGBT is in a short-circuit state and returns the fault to the master computer at the same time. The gate driver will turn off the IGBT according to the order of turning off the transistor outside first and then the transistor inside.



Fig. 5 V_{CE} desaturation detection circuit

◆ Undervoltage protection

The driver board monitors the positive and negative power supply of the secondary side at the same time. When the absolute value of the positive or negative voltage of the secondary side is lower than the threshold voltage, the driving circuit determines that an undervoltage fault has occurred and will feed back a fault signal to the master computer. The gate driver will turn off the IGBT according to the order of turning off the transistor outside first and then the transistor inside.

For IGBT bridge arms, Firstack intelligent gate driver strongly suggests that any IGBT should not work undervoltage. Because of the existence of C_{GC} , when an IGBT in the bridge arm is turned on, its high dv/dt can be coupled to another IGBT through C_{GC} , which leads to a slight turn-on of IGBT. At the same time, low gate voltage will increase the switching loss of IGBT.

Muti-level turn-off (reserved)

In some applications with large stray inductances, such as NPC I-type 3-level large commutation circuit, each time the IGBT is turned off, it will face the risk of excessive turn-off peaks. Due to the limitation of the thermal capacitance of TVS, active clamping technology is not suitable for these occasions, and the muti-level turn-off technology can play a significant role at this time. By using different turn-off resistances during the turn-off process, the entire turn-off process is optimized to suppress the turn-off peak.



Fig. 6 Muti-level turn-off schematic

• Short pulse suppression

In many applications, the module may encounter a short pulse situation, and the IGBT will face the risk of too high turn-off peaks every time the IGBT is turned off by a short pulse. We detect the time of the input signal, when the time is less than 400ns, the signal will be filtered out directly, which needs to be verified according to the actual test situation.

♦ NTC sampling

With the advancement of module packaging technology, more and more modules begin to integrate temperature sensors internally, and NTC is one of these ways. Modules like PrimePACKTM, EconoDUALTM and so on have NTC integrated internally.

The Firstack intelligent gate driver integrates a temperature monitoring circuit that converts the temperature signal into a frequency signal via a voltage-to-frequency conversion circuit, and informs the master computer of the frequency signal via an isolation device.



Fig. 7 Temperature monitoring schematic

The driver core outputs the NTC with the highest temperature among the 12-channel IGBTs to the main control via a frequency signal. The output frequency corresponds to the NTC resistance as follows:

Fout =
$$\left(0.1 + \frac{8 * Rntc}{15 + 11.5 * Rntc}\right) * 32.768$$

*Note: Fout in kHz; Rntc in k Ω .

◆ Fault code return (reserved)

As large-scale grid integration of new energy sources becomes more and more common, the requirements for converter reliability are becoming higher and higher. The statistics of the types and frequency of failures occurring during field operation and the analysis of the causes after serious failures are also becoming more and more important.

The traditional gate driver design, which only informs the master computer that a fault has occurred when a fault occurs, is becoming less and less able to meet customers' needs. In order to provide more fault information to the customers, on the basis of the original 0/1, we have added a fault communication function, which informs the master computer of the fault category and the timing of the fault occurrence by coding.





Fig. 8 Fault communication schematic

The specific fault codes are shown below:

Symbol	Conditions	Min	Туре	Max	Unit	
Fault						
TfaultBlank	FAULT signal fault indication time		5		ms	
Fault Bit no	Fault Bit note: $0 - 15$ If fault is Free, the fault bit holds default high '1'					
0	IGBT 1 (top IGBT) short-circuit fault; 1 for normal; 0 for fault		Bool			
1	IGBT 1 (top IGBT) power supply undervoltage; 1 for normal; 0 for fault		Bool			
2	IGBT 2 (bottom IGBT) short-circuit fault; 1 for normal; 0 for fault		Bool			
3	IGBT 2 (bottom IGBT) power supply undervoltage; 1 for normal; 0 for fault		Bool			
4	IGBT 3 short-circuit fault; 1 for normal; 0 for fault		Bool			
5	IGBT 3 power supply undervoltage; 1 for normal; 0 for fault		Bool			
6	IGBT 4 short-circuit fault; 1 for normal; 0 for fault		Bool			
7	IGBT 4 power supply undervoltage; 1 for normal; 0 for fault		Bool			
8	IGBT 5 short-circuit fault; 1 for normal; 0 for fault		Bool			
9	IGBT 5 power supply undervoltage; 1 for normal; 0 for fault		Bool			
10	IGBT 6 short-circuit fault; 1 for normal; 0 for fault		Bool			
11	IGBT 6 power supply undervoltage; 1 for normal; 0 for fault		Bool			



ED-WP-CB

12(Reserved)	Top IGBT gate monitoring; 1 for normal; 0 for fault	Bool	
13(Reserved)	Bottom IGBT gate monitoring; 1 for normal; 0 for fault	Bool	
14(Reserved)	Overheating fault; 1 for normal; 0 for fault	Bool	
15	Short pulse; 1 for normal; 0 for fault	Bool	



Fig. 9 Fault communication timing diagram

◆ Intelligent fault management system

In NPC I-type 3-level, the DC bus voltage $V_{DC-LINK}$ is higher than the withstand voltage value of any IGBT, so whether in normal operation or fault condition, it must be ensured that the IGBT outside $S_4(S_1)$ is turned off before the IGBT outside $S_3(S_2)$, otherwise $S_3(S_2)$ will be damaged because of withstanding the full DC bus voltage $V_{DC-LINK}$ alone.





Fig. 10 NPC I-type 3-level topology

In the traditional I-type 3-level gate driver design, the correct turn-off timing is generally ensured by the master computer, for example, when a short-circuit fault occurs in S_3 , the driver board first informs the master computer of the fault signal of S_3 , and then the master computer will unify and coordinate the turn-off timing, and thus there are also several risks as follows:

1, Short-circuit protection time exceeds the maximum withstand time of IGBT: S_3 itself short-circuit detection time is generally about 8µs, plus the fault communication time, the master computer filtering time, as well as the turn-off time of S_4 (high-voltage high-power module turn-off time is generally longer, in the range of 4~6µs), the entire protection time will be more than 10µs, which also exceeds the short-circuit safety of the IGBT operating range;

2, Protection is dependent on the master computer: from the single point of failure analysis, when the master computer fails, the protection can not be completed properly, there are security risks.

Another risk is that traditional driver IC and even the vast majority of plug-and-play drivers tend to directly turn off the IGBT in the event of an undervoltage fault, which is not applicable to the NPC I-type 3-level scheme, resulting in a significant safety risk. Based on the analysis above, Firstack has developed a drive solution specifically for NPC I-type 3-levels: by integrating Firstack's unique "intelligent fault management system" on the primary side, it ensures the correct turn-off timing under any operating conditions.



Fig. 11 Intelligent fault management system

The intelligent fault management system will monitor all four PWM signals and all four IGBT status in real time, and then give the optimal operation instruction through Firstack's unique control algorithm. When the whole machine is in continuous operation and the following faults occur, safety can be ensured:

1: PWM command fault: when the master computer is disturbed and sends wrong commands, or the PWM transmission path is disturbed and wrong commands appear on the gate driver side;

2: Connector disconnection: in the operation of the whole machine, the connector is disconnected due to vibration and other factors, resulting in uncontrolled PWM command status;

3: Gate driver power supply abnormality: in the operation of the whole machine, because of the failure of the power supply terminal, causing the gate driver power supply abnormality.4: Short-circuit/undervoltage fault.

Ordering information

ED-WP-CB supports different models of modules from multiple manufacturers. If you have a purchase request, please contact us, and we can provide the gate driver that best meets your needs.

Technical support

Firstack's professional team will provide you with business consultation and technical support. Please contact the Firstack technical sales team if you require the application manual for further information of the technical application.

Legal disclaimer

This manual gives a detailed introduction about the product, but cannot promise to provide specific parameters. No warranty or guarantee, express or implied, is given herein as to the delivery, performance or applicability of the product.

Firstack reserves the right to modify technical data and product specifications at any time without prior notice. Firstack's general payment terms and conditions apply.

Contact information

Tel: +86-571 8817 2737

Fax: +86-571 8817 3973

Website: www.firstack.com

Email: <u>fsales@firstack.com</u>

Address: 4-5/F, Building/5, Xizi Wisdom Park, No.1279 Tongxie Road, Hangzhou, China